

## Z-817 Automatic Antenna Tuner



### Z-817 Automatic Antenna Tuner



The Z-817 is the ultimate autotuner for QRP radios including the Yaesu FT-817(D). The Z-817 interfaces to the CAT port (ACC) on the back of the FT-817 radio with the provided cable. Tuning could not be simpler; one button push on the tuner is all that is needed and the Z-817 takes care of the rest. It will switch to PKT mode, transmit a carrier, tune the tuner, then restore the radio to the previous mode! 2000 memories cover 160 through 6 meters.



Of course, the Z-817 will also function as a general purpose antenna tuner with other QRP radios. Just transmit a carrier and press the tune button on the tuner. The Z-817 is powered by four AA internal Alkaline batteries (not included), so there are no additional cables required to use the Z-817. Latching relays are used so that power consumption is Zero when not tuning allowing a set of batteries to last about one year.

**List Price \$129.99**



### Specifications

- RF Power 0.1 to 20 watts SSB, CW and digital modes.
- Latching relays for ultra low power consumption
- Battery operated 4 x 1.5V Alkaline AA (not included)
- Built-in CAT port interface. CAT thru port for computer connection.
- 2000 memories when used with FT-817 interface (200 memories for other radios)
- 1.8 to 54 MHz coverage (continuous coverage for MARS)
- Tunes 6 to 600 ohms. (16 to 150 on 6M)
- SO-239 in and out connections for dipoles, verticals, beams, G5RV, OCF, Cobra, ect.
- Dimensions: 5.1"L, 4.7"W, 1.7"H. Weight: 9.3 ounces (without batteries).
- Includes 1 foot CAT cable.

### LDG Electronics, Inc.

1445 Parran Rd.

St. Leonard, MD 20685 USA

Phone: 410-586-2177

Fax: 410-586-8475

E-mail: [ldg@ldgelectronics.com](mailto:ldg@ldgelectronics.com)

Web: [www.ldgelectronics.com](http://www.ldgelectronics.com)