

## LDG Electronics Autotuner User Selection Chart

<b>PARAMETERS &amp; FEATURES</b>	<b>Z-817</b>	<b>Z-100+</b>	<b>Z-11ProII</b>	<b>AT-897+</b>	<b>YT-100</b>	<b>KT-100</b>	<b>IT-100</b>	<b>AT-100ProII</b>	<b>AT-200Pro</b>	<b>AT-600Pro</b>	<b>AT-1000Pro</b>
<b>List Price</b>	<b>129.99</b>	<b>159.99</b>	<b>179.99</b>	<b>199.99</b>	<b>199.99</b>	<b>199.99</b>	<b>179.99</b>	<b>229.99</b>	<b>249.00</b>	<b>359.99</b>	<b>599.00</b>
<b>Power Range HF (W)</b>	0.1-20	0.1-125	0.1-125	0.1-100	1-100	1-100	1-100	1-125	5-250	5-600	20-1000
6 meters (max W)	20	100	100	100	100	100	100	100	100	250	250
<b>Good for QRP?</b>	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No	No	No
<b>Good for Backpacking/Portable?</b>	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No	No	No	No
<b>Tuning Range ( )</b>	6-600	6-800	6-1000	6-800	4-800	6-1000	4-800	6-1000	6-800	6-800	6-800
<b>Display</b>											
SWR	1 LED	1 LED	3 LEDs	No	No	1 LED	1 LED	LED Bar	LED Bar	LED Bar	Meter
RF Power	No	No	No	No	No	No	No	LED Bar	LED Bar	LED Bar	Meter
<b>Latching Relays</b>	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No	No	No
<b>Manual Adj. of L&amp;C</b>	No	No	Yes	No	No	No	No	Yes	Yes	Yes	Yes
<b>Antenna Ports</b>	1	1	1	1	1	1	1	2	2	2	2
Antennas Selectable per Port	1	1	1	1	1	1	1	1	4	1	1
Total Antennas Selectable	1	1	1	1	1	1	1	2	8	2	2
<b>Memory Size (data sets)</b>	2000	2000	2,000	2000	2000	2000	2000	4,000	16,000	4,000	4000
# of banks	1	1	1	1	1	1	1	2	8	2	2
<b>Tuning</b>											
Full Tune(sec)	0.5 -3	0.5-6	0.5-6	0.5-6	0.5-6	0.5-6	0.5-6	0.5-6	1.0-6	1.0-6	1.0-8
Memory Tune(sec)	0.5	0.5	0.5	0.5	0.5	0.5	0.5	0.5	1	1	1
Semi (press button to tune)	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Automatic	No	No	Yes	No	No	No	No	Yes	Yes	Yes	Yes
User Auto Threshold Set	No	No	Yes	No	No	No	No	Yes	Yes	Yes	Yes
<b>Internal Battery Capable</b>	Yes	Yes	Yes	No	No	No	No	No	No	No	No
<b>External DC Input Voltage (V)</b>	No	8-18	8-18	No	No	No	No	11-16	11-16	11-16	11-16
<b>Current Draw after Tune</b>	0	<25µA	<25µA	<25µA	<8 mA	<8 mA	<8 mA	<8 mA	Up to 1 A	Up to 1 A	Up to 1 A
<b>Power OFF-ON Switch?</b>	No	No	No	No	No	No	No	No	Yes	Yes	Yes
<b>Weight (lbs)</b>	9.5oz	1	1.5	1.5	1	1	1	1.5	2.5	3.5	6